TECHNAXX® GERMANY

Power Inverter 2000W Sine TE22

For mobile use of various electronic devices via 12V connection

- Power Inverter DC 12V to AC 230V
- LC-Display with Voltagemeter
- 2 xUSB 1 x USB-A, max. 3 A each
- 2000W continously Output Power
- Built-in Ventilation Fan
- 4x120V Sockets
- Overcurrent Protection
- Automatical Turn Off with Alarm
- Real Sine Wave
- High & Low Voltage Protection

- **For mobile use of electronic devices via 12V connection**
- **2x USB ports with max.**
- **6A QC3.0 Charger**
- **4x 120V safety contact sockets with power switch**
- **Converts 12V DC battery power into standard 120V AC (household) power, to run a variety of electronics, e.g. tablets, smartphones, laptop computers, game systems, TVs, DVD/MP3 players, camping accessories, GPS units and much more**
- **Output power max. 2000W (continuous) & 4000W (peak)**
- **Automatic safety shutdown to secure the car battery (alarm at ~10.2V & ~15,8V)**
- **Protection against overload & short circuit**
- **Overheating protection through built-in ventilation**
- **Fixed bracket on device for secure attachment**

Technical Specifications:

- Input voltage of the battery DC 12V (10.2V–15,8V)
- Output voltage per socket AC 120V / AC frequency 50Hz nominal
- Real sine wave
- Circuit protection (DC overload): 6x 40A internal fuses
- Cable length 2x 23.6″
- Weight / Dimensions: 9.3 lbs / (L) 14.2″ x (W) 10.2″ x (H) 4.3″

Package Contents:

Power Inverter 2000W TE22, Fixed bracket on device, 2x 60cm connection cables, User Manual

Article Number: 5045

8 100163 205488