

Power Inverter 2000W Sine TE22

For mobile use of various electronic devices via 12V connection



Power Inverter
DC 12V to AC 230V



LC-Display with
Voltmeter



2 xUSB 1 x USB-A,
max. 3 A each



2000W continuously
Output Power



Built-in
Ventilation Fan



4x120V Sockets



Overcurrent
Protection



Automatic Turn
Off with Alarm



Real Sine Wave



High & Low
Voltage Protection



- For mobile use of electronic devices via 12V connection
- 2x USB ports with max. 6A QC3.0 Charger
- 4x 120V safety contact sockets with power switch
- Converts 12V DC battery power into standard 120V AC (household) power, to run a variety of electronics, e.g. tablets, smartphones, laptop computers, game systems, TVs, DVD/MP3 players, camping accessories, GPS units and much more
- Output power max. 2000W (continuous) & 4000W (peak)
- Automatic safety shutdown to secure the car battery (alarm at ~10.2V & ~15.8V)
- Protection against overload & short circuit
- Overheating protection through built-in ventilation
- Fixed bracket on device for secure attachment

Technical Specifications:

- Input voltage of the battery DC 12V (10.2V–15.8V)
- Output voltage per socket AC 120V / AC frequency 50Hz nominal
- Real sine wave
- Circuit protection (DC overload): 6x 40A internal fuses
- Cable length 2x 23.6"
- Weight / Dimensions: 9.3 lbs / (L) 14.2" x (W) 10.2" x (H) 4.3"

Package Contents:

Power Inverter 2000W TE22, Fixed bracket on device, 2x 60cm connection cables, User Manual



Article Number: 5045

