

Karaoke Microphone BT-X31

Karaoke Bluetooth microphone with stereo speaker

-  Karaoke Mikrofon /
Karaoke Microphone
-  Lautsprecher 2x 3W /
Speaker 2x 3W
-  3.5mm AUX-IN
-  Bluetooth V4.1
-  2000mAh Akku /
2000mAh Battery
-  Karaoke Songs via
Smartphone, Tablet, PC
-  Equalizer (Höhen-, Bass-
& Echoanpassung) /
Equalizer (treble, bass &
echo adjustment)
-  Musikwiedergabe über USB /
Music Playback via USB
-  Musik & Mikrofon
Lautstärkenanpassung /
Music & Microphone
Volume Adjustment








- 2-in-1 Karaoke microphone with two built-in 3W speakers
- Music streaming via Bluetooth V4.1 or AUX-IN (mobile phone, tablets, PC, etc.)
- Compatible with various singing & Karaoke APPs
- Equalizer function (treble, bass & echo adjustment)
- Music & microphone volume adjustment
- Built-in rechargeable 2000mAh battery for portable use
- Easy to use & very stylish design
- The ideal fun: singing with family or friends, for ceremonies & Karaoke parties



Technical specifications:

- Bluetooth V4.1, A2DP profil, ~8m transmitting distance
- Output: 2x 3W stereo speakers, impedance 3Ω, SNR ≤ 80dB
- Frequency range speaker 100Hz~10KHz
- Maximum sound pressure level: >115dB, 1kHz, THD<1%
- USB flash drive (FAT 32) max. 32GB
- Music file format: MP3, WAV
- Rechargeable 2000mAh Lithium polymer battery 4,2V Type 18650
- Charging time ~4-4.5 hours
- Playing time ~3.5-6.5 hours (depending on the volume)
- Micro USB connector for charging
- Connection via Bluetooth or AUX-IN
- Charging voltage / current: DC 5V / 0.5A
- Weight / Dimensions: total 372g / (L) 25 x (B) 7.3 x (H) 7.3cm; Body: (L) 6.9 x (B) 7.3 x (H) 7.3cm

Package Contents:

- MusicMan® Karaoke Microphone BT-X31
- USB-to-Micro USB charging cable
- Audio cable with 3.5mm jack
- User Manual

Article-No. 4685

