

## MINI Power station TX-205+



80 Watt



74 Wh



Modified  
sine wave



DC + USB-A + USB-C PD +  
12V Adapter



LED panel  
and flashlight



Protected  
electronic

**80W AC modified sine wave**  
**LED light panel and flashlight with 3 modes**  
**4 x USB-A (QC3.0), 1x USB-C PD 18W**  
**Battery capacity of 74 Wh**  
**Solar charging compatible (not included)**  
**Protection against overheating,**  
**short-circuit, etc.**

### Technical specifications:

- Li-Ion battery 74 Wh (20,000 mAh, 3.7 V)
- Power supply (input) 19 V DC, 1.5 A
- Solar panel (input) 15-24 V DC, 1.2 A, 21W (max.)
- USB-A output 1 & 3: 5 V DC/3 A Total: 5 V, 6.6 A (max.)
- USB-A output 2 & 4: 5 V DC/3 A, 9 V DC/ 2 A, 12 V DC/1.5 A; QC3.0 18 W (max.)
- USB-C output: 5 V DC/3 A, 9 V DC/ 2 A, 12 V DC/1.5 A; PD 3.0, 18 W (max.)
- DC output: 12-16.8 V DC, 10 A (10.8 A max.)
- AC output: 220 V, 50 Hz, 120 W (max.)
- AC waveform: modified sine wave
- AC nominal power / peak power: 80 W / 120 W
- Charging time approx. 5 hours
- Operating temperature: -10°C to 40°C
- Protected against: Short circuit, overheating, overcharge, overvoltage, undervoltage, overcurrent
- Flashlight: 1 W, 120 lm; 3 functions
- LED panel 90 lm / 120 lm
- Connections: 1 x DC output (DC5521), 4 x USB-A output, 1 x USB-C output, 1 x 230 V output, 1 x DC input (DC35135)
- Dimensions / Weight: 14.5 x 10.5 x 7.7 cm / 1.2 kg

### Package Contents:

Technaxx MINI Power Station TX-205+,  
AC adapter, 12V DC adapter, user manual

Article-No. 5014

