


Power Inverter 1200W TE16

For mobile use of various electronic devices via 12V connection



12V / 230V Power Inverter
DC 12V to AC 230V

max 3.1A 2x 5V Output
USB Ports

2x 230V 2x 230V Sockets
with Power Switch

High & Low Voltage Protection

1200W 1200W continuously
Output Power

Overcurrent Protection

Automatical Turn Off with Alarm

Built-in Ventilation Fan

Modified sine wave

- 2x 5V USB ports with max. 3.1A (in total)
- 2x 230V safety contact sockets with power switch
- Converts 12V DC battery power into standard 230V AC (household) power, to run a variety of electronics, e.g. tablets, smartphones, laptop computers, game systems, TVs, DVD/MP3 players, camping accessories, GPS units and much more
- Output power max. 1200W (continuous) & 2400W (peak)
- Automatic safety shutdown to secure the car battery (alarm at ~10.5V & ~16V)
- Protection against overload & short circuit
- Overheating protection through built-in ventilation

Technical Specifications:

- Input voltage of the battery DC 12V (10.5V–16V)
- Output voltage per socket AC 230V / AC frequency 50Hz nominal
- Modified sine wave
- Circuit protection (DC overload): 3x 40A internal fuses
- Cable length 2x 90cm
- Weight / Dimensions: 2.3 kg / (L) 28.8 x (W) 15.9 x (H) 9.9cm

Package Contents:

- Power Inverter 1200W TE16
- 2x 90cm connection cables
- User Manual



Article-No. 4753

