Wireless TV Chin Guard Headphone TX-99

Stereo headphone as hearing aid for voice & music















Funk Stereokopfhörer / Wireless Headphone



Sender & Empfänger / Transmitter & Receiver



Hörunterstützung / Hearing aid



Verbindung zum Wiedergabegerät via Audiokabel / Connection to playback device via audio cable



Mikrofonanschluss / Microphone jack



Line-in/out Anschluss / Line-in/out jack



Reduzierung von Umgebungsgeräuschen / Environmental Noise Reduction



3 Ohrsteckergrößen / 3 Ear Plug Sizes



470mAh Akku / 470mAh Battery

- Wireless transmission between transmitter and receiver up to 15m open areas
- Connectable to nearly every device with an audio output via 3.5mm audio cable jack-on-RCA
- Hearing aid & adequate volume for TV and music

 Connection to a mobile phone via AUX cable

• In-Ear headphone for effective environmental noise reduction

Ideal for hearing impaired persons



Technical Specifications:

- Transmission distance ~15m (open areas)
- Frequency band (FM channels): 863.5, 864, 864.5MHz
- \bullet Frequency response / THD: 20Hz–20kHz / < 5% at 1kHz
- Radiated transmission power 5mW maximum Impedance: $32\Omega \pm 15\%$ at 1kHz
- Sensitivity: 114 ± 5dB at 1kHz
- Ports: Microphone 2.5mm & Line-in/out 3.5mm
- Built-in rechargeable 470mAh lithium polymer battery 3.7V
- Charging time ~3 hours / Playing time ~8 hours
- Material: Silicone + PP + TPE + ABS plastic
- Receiver Weight / Dimensions: 64g / (L) 16.7 x (W) 1.9 x (H) 20.6cm
- Transmitter Weight / Dimensions: 86g / (L) 13.2 x (W) 5.0 x (H) 3.8cm (without antenna) / (H) 9.5cm (with antenna)

Package Contents

Wireless TV Chin Guard Headphone TX-99 (transmitter & receiver), Power adapter 5V/1A, 2.5mm cable with microphone, 3.5mm 3-Pin audio cable, 3.5mm audio cabel to 2 female 3.5mm RCA jack & 2 male 3.5mm RCA jack, 3 different earplug sizes, User Manual

Article-No. 4735

