











Wireless Security Alarm-Set TX-104

Receiver with 2 sensors for motion detection



-  Kabellose Übertragung / Wireless Transmission
-  Auslösezeit Sensor 0,5 Sekunden / Trigger Time Sensor 0.5 seconds
-  Erweiterbar bis zu 5 Sensoren / Expandable up to 5 Sensors
-  Einstellbare Bewegungserfassung / Adjustable Motion Detection
-  Alarm mit Ton / Sound Alarm
-  Erfassungswinkel 70° / Detection Angle 70°
-  Vibrationsalarm / Vibration Alarm
-  Alarm mit LED-Licht / LED Light Alarm
-  Sensor-Schutzklasse IP66 / Sensor Protection Class IP66
-  Batteriebetrieb / Powered by Batteries

- Wireless transmission range up to 100m between receiver and sensor
- Very short sensor trigger time 0.5 seconds
- Expandable up to 5 sensors with one receiver
- Adjustable sensor motion detection distance up to 12m
- 70° detection angle of sensor
- 3 alarm methods: vibration, sound, LED light
- Sensor protection class IP66 (dust & water proof)
- Receiver with belt buckle
- Mounting buckle 180° rotatable
- Powered by batteries* (*not included)
- Functional & easy handling



Technical specifications:

- Sensor power consumption $\leq 2\text{mA} / 4.5\text{V}$
- Sensor PIR distance $\sim 12\text{m}$, angle 70° , trigger time 0.5 sec.
- Sensor signal strength $\leq 10\text{mW}$
- Sensor IP66 protection class
- Sensor power supply: 3x AAA batteries* (*not included)
- Sensor battery life ~ 400 hours (~ 16 days)
- Sensor standby time ~ 6 month (if nothing is detected)
- Receiver power consumption $\leq 8\text{mA} / 4.5\text{V}$
- Receiver power supply: 3x AAA batteries* (*not included)
- Receiver battery life ~ 100 hours (~ 4 days)
- Receiver alarm: vibration or sound 15 sec. or LED light
- Transmission frequency: 433MHz wireless
- Working temperature: -20° up to $+60^\circ\text{C}$
- Sensor: 132g / (L) 14 x (W) 10 x (H) 4cm
- Receiver: 82g / (L) 8 x (W) 5.5 x (H) 4cm

Package Contents:

- Wireless Security Alarm Set TX-104 (1 receiver & 2 sensors)
- 2 Mounting belts
- User Manual

Article-No. 4750

